A method for reversing the laser modulation in a Storage ring

Weihang Liu, Yu Zhao, Yi Jiao,* and Sheng Wang[†]

Key Laboratory of Particle Acceleration Physics and Technology,

Institute of High Energy Physics, Chinese Academy of Sciences, Beijing 100049, China and

Spallation Neutron Source Science Center, Institute of High Energy Physics, Chinese Academy of Sciences

Chao Feng

Shanghai Institute of Applied Physics, Chinese Academy of Sciences, Shanghai 201800, China and Shanghai Advanced Research Institute, Chinese Academy of Sciences, Shanghai 201210, China

The pursuit of coherent radiation generation remains a central focus in advancing storage ring light sources. Despite the promise of laser modulation in achieving this goal, it brings about a noticeable decline in beam quality. Efforts to mitigate this decline have resulted in the proposal of demodulation schemes. However, implementing modulation and demodulation within the storage ring presents significant challenges due to dynamical and spatial constraints within straight sections. In this study, we propose a straightforward and easily implementable method for achieving reversible laser modulation in a storage ring. Notably, our approach circumvents the need for special storage ring requirements, such as lengthy straight sections or bypass section. Simulation results demonstrate a substantial restoration of beam quality following demodulation. This innovative scheme holds great promise for the realization of high repetition rate coherent storage ring light sources.

I. INTRODUCTION

As a crucial experimental tool for scientific inquiry, the performance of light sources continues to evolve in tandem with scientific progress. Notably, particle accelerator-based light sources are continually advancing their technology and capabilities to meet the demands of scientific exploration. The free electron laser (FEL) exemplifies this progression, transitioning from normal conducting accelerators to superconducting accelerators. This upgrade has significantly increased the repetition rate of radiation pulses by nearly five orders of magnitude [1]. Furthermore, leveraging sophisticated beam manipulation techniques, FELs now offer temporal resolutions on the scale of attoseconds [2], empowering attosecond science with an unparalleled tool.

Similarly, the Storage Ring Light Source (SRLS) has also undergone significant enhancements. By adopting the multibend achromat (MBA) design [3], SRLS has achieved a substantial reduction in its natural emittance, approaching the diffraction limit of X-rays. Consequently, the brightness of the light source has surged by more than two orders of magnitude, heralding a new era of enhanced performance and capabilities.

The high repetition rate, multi-user capability and high stability of SRLS make it more attractive than FEL. However, its longitudinal coherence and time resolution are still not comparable to FELs. At present, the time resolution of SRLS is basically in the picosecond range or longer. In addition, its energy resolution is also limited by the monochromator technology, which is difficult to break through to the millielectronvolt scale. These limitations have made it difficult to meet some of the needs of current and future scientific research, and it is therefore necessary to be improved.

The generation of microbunches via laser modulation represents a viable solution for fulfilling this requirement. By interacting the beam with a laser in a modulator, the beam is given an energy modulation. This energy modulation is converted to density modulation after the beam passes through a longitudinal dispersion section. This density modulated beam will generating coherent radiation in the downstream undulator at high harmonic of the laser [4–8]. Due to the properties of coherent radiation, the radiated power is proportional to the square of the beam charge and the pulse duration is proportional to the modulated laser pulse duration. These properties capable of generating radiation pulses with high power and variable duration.

By combining the "flat" nature of the storage ring, i.e., its ultra-low vertical emittance, numerous laser modulation schemes better suited for the storage ring have been proposed. For instance, vertical momentum (or angular) modulation can be induced in the beam using a TEM01 or tilted incidence laser [9–11]. This modulation can then be converted into density modulation as the beam traverses through a dispersion section, benefiting from the ultra-low vertical emittance, which significantly enhances the density modulation. Furthermore, energy modulation schemes can also benefit from the ultra-low vertical emittance. One such method, called angular dispersion microbunching generation (ADM) [12], utilizes a dipole to couple the longitudinal and transverse motion of an electron prior to energy modulation. The resultant energy modulation is then converted into density modulation through a Dogleg. This approach has been implemented in the straight section of a storage ring to generate coherent radiation [13, 14].

Regardless of the type of modulation, it will inevitably have an effect on the beam, which will degrade the beam

^{*} jiaoyi@ihep.ac.cn

[†] wangs@ihep.ac.cn

quality. This makes it difficult to modulate the beam continuously or at high frequencies, thus limiting the repetition rate. To solve this problem, demodulation schemes have been proposed [15, 16]. It restores the beam quality by demodulating the modulated beam.

The demodulation process for energy modulation is relatively simple compared to angular modulation. Therefore, choosing an ADM modulation scheme makes it easier to design a demodulation transport. However, considering the complexity of the storage ring dynamics and the limited space of the straight sections, it is extremely challenging to design a reversible ADM within a storage ring. The main difficulty is to design an isochronous transport between energy modulation and demodulation. This requires sufficient space on the one hand and a delicate design on the other to avoid excessive impact on the storage ring dynamics.

There are two ways to handle this difficulty, one is by designing a dedicated long straight section storage ring [16]. The other is to place the reversible ADM in the bypass of the storage ring [15]. The bypass design requires frequent injection and extraction to achieve coherent radiation, and the technical constraints of the injection and extraction elements impose limitations on the achievable repetition rate. On the other hand, designing a dedicated long straight section is not a standard requirement for a typical SRLS.

To enable the implementation of a reversible ADM in a typical storage ring, this paper presents a simple scheme. In this approach, the ADM and the demodulation section are situated in distinct straight sections, while an isochronous transport is established using arc sections and a horizontal chicane positioned between the ADM and the demodulation sections. The feasibility of the scheme is verified through simulations based on the parameters of the southern advanced photon source (SAPS) [17]. Post-modulation, a bunching factor of 14% at the 10th harmonic is achievable, demonstrating sufficient capability for producing coherent radiation. Following demodulation, beam parameters are largely restored, with only a minor increase of 0.04% in energy spread and 10.6% in vertical emittance. The beam can return to its equilibrium state after approximately 150 turns, with a corresponding repetition rate of up to 1.1MHz.

II. REVERSIBLE ADM IMPLEMENTED IN STRAIGHT SECTIONS OF A STORAGE RING

When considering the number of beamlines and associated construction costs, it is common practice to restrict the length of straight sections in a typical storage ring to 5-6 meters. In order to achieve reversible ADM in such storage rings, it is necessary to place modulation and demodulation in separate straight sections. Typically, storage rings are multi-period structures; for instance, the SAPS has a period of 32. In this configuration, the ADM section and the demodulation section are positioned in two adjacent periods, with a horizontal chicane situated between them in the straight section, as illustrated in Fig. 1.



FIG. 1. Layout of a reversible ADM in a storage ring.

This layout enables the achievement of isochronous transport from the modulation section to the demodulation section. Following energy modulation in the ADM section, the beam proceeds through downstream components including a dogleg, radiator, and dipoles, contributing to the longitudinal dispersion $R_{56,adm}$ in the isochronous transport. Subsequently, the beam traverses the first arc region after the ADM section to reach the horizontal chicane. It then passes through the second arc region to access the demodulation section. Within the demodulation section, the beam encounters two vertical dipoles before reaching the modulator, which also imparts longitudinal dispersion $R_{56,demodu}$. Summing all longitudinal dispersion contributions yields the total longitudinal dispersion of the isochronous transport, $R_{56,tot} = R_{56,adm} + 2R_{56,r} + R_{56,c} + R_{56,demodu}$, where $R_{56,r}$ and $R_{56,c}$ represent the arc and chicane longitudinal dispersion, respectively. Following the isochronous requirement, we obtain

$$\begin{cases} R_{53,tot} = 0\\ R_{54,tot} = 0.\\ R_{56,tot} = 0 \end{cases}$$
(1)

The achievement of zero $R_{56,tot}$ benefits from the factor that the longitudinal dispersion $R_{56,r}$ of a typical storage ring arc section is opposite in sign to the other contributing terms of $R_{56,tot}$.

Given the ADM parameters, the isochronous requirement can be achieved by adjusting the dipole angle θ of the chicane dipoles and the angles θ_4 and θ_5 of the two dipoles upstream of the modulator in the demodulation section. It's worth noting that both the modulation and demodulation sections are located in straight sections, so $R_{51,tot}$ and $R_{52,tot}$ naturally become zero.

The ADM section needs to be designed to target the coherent radiation performance or the magnitude of the bunching factor for a particular harmonic. The ADM bunching factor is related to the beam parameters as:

$$b(n) = J_n \left(nk_L r_{56} A \right) \exp\left[-\frac{1}{2} (nk_L \eta)^2 \gamma_y \varepsilon_y\right], \qquad (2)$$

where r_{56} and η are the dogleg vertical and longitudinal dispersions of the ADM, respectively, A is the modulation strength, γ_y is the twiss parameter of the ADM entrance in the vertical direction, and ϵ_y is the vertical emittance.

Equation (2) indicates that the storage ring vertical emittance should be controlled at a relatively low level to obtain a sufficiently large bunching factor. Since both the ADM section and the demodulation section contribute to the vertical dispersion, the dipoles, modulators, and radiator in both sections contribute to the quantum excitation, increasing the vertical emittance:

$$\varepsilon_y \propto \int_{dipole,modu,rad} \frac{H_y}{|\rho|^3} ds,$$
 (3)

where H_y is the vertical chromatic H-function. The most effective way to reduce the growth of vertical emittance is to minimize the dispersion of these two sections.

The layout of the ADM section, as depicted in Fig. 2, consists of five dipoles, a modulator, and a radiator. To ensure achromatic conditions and coaxiality of the entrance and exit beams, the deflection angle and spacing of the dipoles must satisfy the following

[18]:

$$\begin{cases} b(L_1 + L_2 + L_3 + L_4 + \frac{9L_b}{2}) + (L_2 + L_b)\theta_1 + \left(L_4 + \frac{3}{2}L_b\right)\theta_2 + \frac{1}{2}L_b\theta_3 = 0\\ b + \theta_2 + \theta_3 = 0 \end{cases}$$
(4)



FIG. 2. Layout of an ADM in a straight section.

Here, $b, \theta_1, -\theta_1, \theta_2, \theta_3$ correspond to the deflection angles of the first to the fifth dipole, L_i (i = 1, 2, 3, 4) represents the distance between the dipoles, and L_b represents the length of each dipole.

Under these conditions, combined with the ADM optimality condition [12]

$$\begin{cases} r_{56} + b\eta = 0\\ 1 + Ak_L r_{56} = 0 \end{cases}$$
 (5)

It can be observed that the dispersion of the ADM section is positively correlated with the deflection angle b, while the bunching factor is also positively correlated with b. Therefore, there is a trade-off between low dispersion and a high bunching factor. Given the modulation strength, one can optimizing the bunching factor to finding deflection angle b or to choose a small enough one.

The demodulation section has a similar layout of the ADM section by comprises only four dipoles and a modulator. Once the parameters of the ADM section are defined, the parameters of the two dipoles preceding the modulator are exclusively determined by the isochronous condition (see Eq. 1). Similarly, the parameters of the last two dipoles are determined by the achromatic and coaxial conditions.

The method described above enables the conduct of reversible ADM designs for typical storage rings. This approach is highly versatile and can be applied to a wide range of multi-periodic storage rings.

III. REVERSIBLE ADM BASED ON SAPS

To demonstrate the proposed scheme, we utilize the SAPS storage ring for reversible ADM design. It's worth noting that while this design may not be optimal, it sufficiently showcases the proposed approach. The SAPS storage ring operates at an energy of 3.5 GeV with a natural emittance of 33 pm and a straight section length of 6 m.

In the ADM section, we adopt an energy modulation intensity of 0.1% (initial energy spread) and a modulated laser wavelength of 266 nm. Somewhat arbitrarily, the deflection angle of the first dipole in the ADM section is set to 5 mrad. Given the limited space available in the straight sections, the modulator has a period of 1 with a length of 0.25m. The radiator has a period of 7 with a length of 0.84 m, which will radiate at a wavelength of 26.6 nm. With these parameters, the maximum dispersion of the ADM section is calculated to be approximately 11 mm, which contributes to a vertical emittance of about 0.58 pm, as illustrated in Fig. 3.

To achieve isochronous transport between the modulation and the demodulation, the chicane parameter θ and the parameters θ_4 , θ_5 of the dipoles upstream of the





FIG. 3. Vertical dispersion and H-function of the ADM section.



FIG. 4. Vertical dispersion and *H*-function of the chicane section (up) and the demodulation section (down).

modulator in demodulation section are set to 13.8 mrad, 9.6 mrad, and -6.7 mrad, respectively. Other parameters are detailed in the Appendix. These specified parameters result in a horizontal dispersion of 37 mm, corresponding to an increase in horizontal emittance by 2.67 pm. Additionally, the demodulation section contributes a vertical dispersion of 22.5 mm, resulting in an increase in vertical emittance by 0.75 pm, as shown in Fig. 4. The final emittances are 36.7 pm in the horizontal direction and 1.32 pm in the vertical direction.

We adopted the ELEGANT [19] code to proceeding laser modulation and tracking the modulated beam through the ADM section, arc, chicane and the demodulation section. After the density modulation, the bunching factor in versus the harmonic number is illustrated in Fig. 5. It can be observed that the 10th harmonic bunching factor is up to 14%.

Following demodulation, the beam's phase space is essentially restored. This is attributed to the achievement of isochronous transport, as shown in Fig. 6, where from the center of the ADM modulator to the center of the modulator in demodulation, $R_{5i,tot} = 0$ (i = 1,2,3,4,5,6). Additionally, the residual energy modulation amplitude is less than 0.04%. When considering only linear terms of the transport and treating the energy modulation as



FIG. 5. Bunching factor at different harmonic number.

an equivalent sinusoidal point kick, following demodulation, the increase in energy spread is 0.025%, and the increase in vertical emittance is 1.8%, both of which are nearly negligible. However, in a more realistic scenario that accounts for nonlinear terms of the transport, 3D laser-electron beam interaction, and finite-length modulators, the increase in energy spread rises to 0.04%, and the increase in vertical emittance to 10.6%, indicating a significant growth compared to the ideal case. This indicates a strong influence of nonlinear terms, and further reduction in parameters growth may be achievable by appropriately optimising the multipole magnets in the arc section. Nevertheless, this would likely compromise the symmetry of the ring and potentially affect its dynamics, addressing this issue may require different strategies and is beyond the scope of this paper. Therefore, we leave it for future work.

Eventually, the demodulated beam returns to the equilibrium state after about 150 turns under damping, corresponding to a time of about 410 microseconds. Given that the storage ring contains 450 bunches, the SAPS reversible ADM can achieve a maximum repetition frequency of approximately 1.1 MHz.

In the ADM section, the modulated beam will produce coherent radiation after passing through the radiator. To demonstrate the tunability of the radiation duration, we modulate the electron beam with two lasers of different durations, respectively.

Under modulation with a laser of 100 fs duration, simulated using the GENESIS code [20], a radiation pulse with a peak power of about 0.7 MW and a bandwidth of 14.4 meV can be generated. Considering a repetition rate of 1.1 MHz, the average flux reaches 2.3×10^{12} . If a modulation laser with a duration of 700 fs (with the same peak power) is used, picosecond pulse output can be achieved with the bandwidth reduced by approximately one order of magnitude, to about 1 meV. Additionally, the average flux increases by nearly an order of magnitude, reaching 1.4×10^{13} , as depicted in Fig. 7.

IV. DISCUSSION AND CONCLUSION

We propose an easy-to-implement method to achieve reversible laser modulation in storage rings. This scheme utilizes two arcs and three straight sections of the stor-



FIG. 6. Transfer matrix terms R_{53} , R_{54} and R_{56} along the beam line between the center of modulator and demodulator.



FIG. 7. Radiation pulse and the spectrum for the case of 100 fs duration seed laser (up) and 700 fs duration seed laser (down).

age ring. By incorporating a chicane within one of the straight sections, an isochronous transfer from the modulation section to the demodulation section is achieved, thereby eliminating energy modulation. Based on SAPS parameters, we present a design. The results indicate that after beam modulation, a 14% bunching factor can be achieved at the 10th harmonic. Under modulation by different duration laser, 100 fs to several picoseconds radiation pulse can be a achieve with large average flux.

After demodulation, the beam parameters largely recover, but compared to the ideal case, the increase in beam energy spread and vertical emittance, appears larger. This discrepancy is contributed by higher-order terms in the transport. Future efforts could explore reducing this discrepancy by locally optimizing the nonlinear elements in the arcs. At the current growth rate, beam recovery requires approximately 410 microseconds, allowing for a repetition rate of up to 1.1 MHz.

It is noteworthy that the reversible ADM has some ef-

fects on the storage ring dynamics. Since the longitudinal dispersion of the transport between modulation and demodulation is zero, the momentum compression factor of the whole ring will be reduced. This reduction will have some effect on the longitudinal dynamics, although in our case the momentum compression factor is only reduced by $2/32 \sim 6\%$ due to the multiple periods of the SAPS, and the effect on the longitudinal dynamics is negligible. For storage rings with a few periods, e.g., only two periods, this effect is significant. For this kind of storage ring design, Steady-State Microbunching related studies can be used as a guide [21, 22]. The calculations demonstrate reductions in both the dynamic aperture (DA) and the local momentum apertures (MA). However, the decrease in DA is less than 10%, while the MA remain greater than 4%. These changes have a negligible impact on the routine operation of the storage ring.

In addition, the scheme utilizes three straight sections and two arcs, which presents a clear disadvantage in terms of beamline utilization. This issue could be addressed by designing a storage ring with longer straight sections, thereby enabling the scheme to be implemented with only two straight sections. Alternatively, longitudinal dispersion of the chicane could be achieved by utilizing the horizontal components of the dipoles in the ADM and demodulation sections, although this approach may increase the complexity of mechanical alignment. Further research into more effective solutions to this challenge is warranted.

Nevertheless, in this study, we have not considered the influence of collective effects, such as intra-beam scattering and radiation effects from the radiator. The latter are relatively weak under the parameters considered in this study. Additionally, IBS affects the beam emittance, which is energy-dependent. For low-energy storage rings, the impact of IBS cannot be disregarded. Therefore, when designing reversible ADM, it is recommended to consider IBS as well. To achieve the full implementation of reversible ADM, further detailed investigations are necessary. These will be pursued as part of our future research endeavours.

ACKNOWLEDGMENTS

This work was supported by the Basic and Applied Basic Research Foundation of Guangdong Province (No. 2019B1515120069), National Natural Science Foundation of China (Nos. 12275284 and 11922512), and Youth Innovation Promotion Association of the Chinese Academy

- W. Decking, S. Abeghyan, P. Abramian, *et al.*, A MHzrepetition-rate hard X-ray free-electron laser driven by a superconducting linear accelerator, Nature Photonics 14, 391 (2020).
- [2] J. Duris, S. Li, T. Driver, et al., Tunable isolated attosecond X-ray pulses with gigawatt peak power from a free-electron laser, Nature Photonics 14, 30 (2020).
- [3] D. Einfeld, M. Plesko, and J. Schaper, First multi-bend achromat lattice consideration, Journal of Synchrotron Radiation 21, 856 (2014).
- [4] B. Girard, Y. Lapierre, J. M. Ortega, et al., Optical Frequency Multiplication by an Optical Klystron, Physical Review Letters 53, 2405 (1984).
- [5] G. De Ninno, E. Allaria, M. Coreno, et al., Generation of Ultrashort Coherent Vacuum Ultraviolet Pulses Using Electron Storage Rings: A New Bright Light Source for Experiments, Physical Review Letters 101, 053902 (2008).
- [6] C. Evain, A. Loulergue, A. Nadji, J. M. Filhol, M. E. Couprie, and A. A. Zholents, Soft x-ray femtosecond coherent undulator radiation in a storage ring, New Journal of Physics 14, 023003 (2012).
- [7] W.-H. Liu, G.-Q. Zhou, and Y. Jiao, Generating femtosecond coherent X-ray pulses in a diffraction-limited storage ring with the echo-enabled harmonic generation scheme, Nuclear Science and Techniques 29, 143 (2018).
- [8] X. Yang, G. Penn, L. H. Yu, V. Smaluk, and T. Shaftan, Optimization of echo-enabled harmonic generation toward coherent EUV and soft X-ray free-electron laser at NSLS-II, Scientific Reports 12, 9437 (2022).
- [9] D. Xiang and W. Wan, Generating Ultrashort Coherent Soft X-Ray Radiation in Storage Rings Using Angular-Modulated Electron Beams, Physical Review Letters 104, 084803 (2010).
- [10] X. Wang, C. Feng, T. Liu, Z. Zhang, C.-Y. Tsai, J. Wu, C. Yang, and Z. Zhao, Angular dispersion enhanced prebunch for seeding ultrashort and coherent EUV and soft X-ray free-electron laser in storage rings, Journal of Synchrotron Radiation 26, 677 (2019).
- [11] Y. Lu, X. Wang, X. Deng, C. Feng, and D. Wang, Methods for enhancing the steady-state microbunching in stor-

of Sciences (No. Y201904).

Appendix A: Parameters table of the Reversible ADM section

age rings, Results in Physics 40, 105849 (2022).

- [12] C. Feng and Z. Zhao, A Storage Ring Based Free-Electron Laser for Generating Ultrashort Coherent EUV and Xray Radiation, Scientific Reports 7, 4724 (2017).
- [13] C. Li, C. Feng, and B. Jiang, Extremely bright coherent synchrotron radiation production in a diffraction-limited storage ring using an angular dispersion-induced microbunching scheme, Physical Review Accelerators and Beams 23, 110701 (2020).
- [14] W. Liu, Y. Zhao, Y. Jiao, and S. Wang, Generating high repetition rate X-ray attosecond pulses in a diffraction limited storage ring, Scientific Reports 13, 14019 (2023).
- [15] B. Jiang, C. Feng, C. Li, Z. Bai, W. Wan, D. Xiang, Q. Gu, K. Wang, Q. Zhang, D. Huang, and S. Chen, A synchrotron-based kilowatt-level radiation source for EUV lithography, Scientific Reports 12, 3325 (2022).
- [16] Z. Li, X. Deng, Z. Pan, C. Tang, and A. Chao, Generalized longitudinal strong focusing in a steady-state microbunching storage ring, Physical Review Accelerators and Beams 26, 110701 (2023).
- [17] Y. Zhao, Y. Jiao, and S. Wang, Design study of APS-Utype hybrid-MBA lattice for mid-energy DLSR, Nuclear Science and Techniques 32, 71 (2021).
- [18] F. Zeng, Y. Jiao, W. Liu, and C.-Y. Tsai, An asymmetric four-bend S-chicane compressor immune to coherent synchrotron radiation effects (2024), arXiv:2403.06101 [physics].
- [19] M. Borland, ELEGANT: A flexible SDDS-compliant code for accelerator simulation, Advanced Photon Source LS-287 (2000).
- [20] S. Reiche, GENESIS 1.3: a fully 3D time-dependent FEL simulation code, Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment 429, 243 (1999).
- [21] X. Deng, A. Chao, J. Feikes, A. Hoehl, *et al.*, Experimental demonstration of the mechanism of steady-state microbunching, Nature **590**, 576 (2021).
- [22] X. Deng, Steady-State Micro-Bunching based on Transverse-Longitudinal Coupling (2024), arXiv:2404.06920.

Parameter	Value	Unit
Ring		
R _{56,r}	0.638	mm
Damping time $(\tau_x, \tau_y, \tau_\delta)$	13.7, 20.5, 13.6	ms
Peak current	110	А
ADM section		
Dipole		
Bending angle	5	mrad
Length	0.2	m
Dogleg		
Bending angle	5.214	mrad
Length	0.2	m
Distance between dipoles	1.424	m
Modulator		
Peak field	0.6	Т
Period	0.25	m
Period number	1	
Radiator		
Peak field	0.54	Т
Period	0.12	m
Period number	7	
Laser		
Peak power	65	GW
Waist size	0.2	mm
Duration	100 - 700	\mathbf{fs}
Chicane		
Dipole Bending angle	13.8	mrad
Dipole Length	0.2	m
Distance between first and second dipoles	2.5	m
Demodulation section	n	
First dipole length	0.2	m
First dipole angle	9.6	mrad
Second dipole length	0.2	m
Second dipole angle	-6.7	mrad
Distance between first and second dipole	2	m
Third dipole length	0.2	m
Third dipole angle	-11	mrad
Distance between second and third dipole	0.4	m
Fourth dipole length	0.2	m
Fourth dipole angle	-8.15	mrad
Distance between third and fourth dipole	2.6	m

TABLE I. Parameters of the Reversible ADM section